



## Dual Range Non-Contact Voltage Tester 12 to 1000V AC



The NCVT-2P is a non-contact voltage tester that detects 12 to 1000V AC and indicates the presence of voltage in cables, cords, circuit breakers, light fixtures, switches, outlets and wires as well as AC voltage in doorbells, thermostats, low voltage lighting and irrigation systems. Includes both visual and audible signals. The NCVT-2P is rugged enough for any job site.

### Specifications

<b>Type:</b>	Dual Range	<b>Application:</b>	Non-Contact Detection and Testing of AC Voltage
<b>Special Features:</b>	LED and Audible Beep Indications, Auto-Power Off, Pocket Clip	<b>Material:</b>	Polycarbonate
<b>Drop Protection:</b>	6.6' (2 m)	<b>Voltage:</b>	12 – 1000V AC; 70 – 1000V AC
<b>Frequency:</b>	50 - 500 Hz	<b>Pollution Degree:</b>	2
<b>Ingress Protection:</b>	IP54	<b>Standard:</b>	CAT IV 1000V
<b>Included:</b>	NCVT; Batteries	<b>Batteries:</b>	2 x AAA
<b>Battery Life:</b>	142 hr	<b>Overall Length (Inch):</b>	5.82
<b>Overall Length (cm):</b>	14.8	<b>Overall Height (Inch):</b>	0.86
<b>Overall Height (cm):</b>	2.2	<b>Overall Width (Inch):</b>	1.09
<b>Overall Width (cm):</b>	2.8	<b>Weight (oz):</b>	1.7
<b>Weight (g):</b>	48		